

Troffer and Strip Fixture Retrofit Options

Fixture Type	Size/Lamps	Lens	Lamps	Watts	Internal Driver Solution	Watts	DLC Model Number	External Driver Solution	Watts	DLC Model Number
Troffer	1x4x1	Prismatic	1 x F32TNBF	28	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Troffer	1x4x1	Prismatic	1 x F34T12STM	50	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Troffer	1x4x1	Prismatic	1 x F40T12STM	57	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Troffer	1x4x2	Prismatic	2 x F32T8NBF	56	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL4100+ Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	1x4x2	Prismatic	2 x F34T12STM	100	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL4100+ Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	1x4x2	Prismatic	2 x F40T12STM	114	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL4100+ Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	2x2x2	Prismatic	2 x F32T8 U-Bend	56	2 x LMK209	18	LMK209-F-xxxxK-2	1 x SY18W & 2 x SL2080	18	SY18W-2-SL2080-F-xxxxK-T
Troffer	2x2x2	Parabolic	2 x F32T8 U-Bend	56	3 x LMK206	18	LMK206-F-xxxxK-3	1 x SY18W & 3 x SL2080	18	SY18W-3-SL2080-F-xxxxK-T
Troffer	2x2x3	Prismatic	3 x F17T8NBF	64	2 x LMK209	18	LMK209-F-xxxxK-2	1 x SY18W & 2 x SL2080	18	SY18W-2-SL2080-F-xxxxK-T
Troffer	2x2x3	Parabolic	3 x F17T8NBF	64	3 x LMK206	18	LMK206-F-xxxxK-3	1 x SY18W & 3 x SL2080	18	SY18W-3-SL2080-F-xxxxK-T
Troffer	2x2x2	Prismatic	2 x F40T12 U-Bend	114	2 x LMK209	18	LMK209-F-xxxxK-2	1 x SY18W & 2 x SL2080	18	SY18W-2-SL2080-F-xxxxK-T
Troffer	2x2x2	Parabolic	2 x F40T12 U-Bend	114	3 x LMK206	18	LMK206-F-xxxxK-3	1 x SY18W & 3 x SL2080	18	SY18W-3-SL2080-F-xxxxK-T
Troffer	2x2x3	Prismatic	3 x F20T12STM	78	2 x LMK209	18	LMK209-F-xxxxK-2	1 x SY18W & 2 x SL2080	18	SY18W-2-SL2080-F-xxxxK-T
Troffer	2x2x3	Parabolic	3 x F20T12STM	78	3 x LMK206	18	LMK206-F-xxxxK-3	1 x SY18W & 3 x SL2080	18	SY18W-3-SL2080-F-xxxxK-T
Troffer	2x2x3 -Biax	Prismatic	3 x F40BXE	102	3 x LMK213	36	LMK213-F-xxxxK-3	Not DLC Listed		Not DLC Listed
Troffer	2x2x3 -Biax	Parabolic	3 x F50BXE	162	3 X LMK213	36	LMK213-F-xxxxK-3	Not DLC Listed		Not DLC Listed
Troffer	2x4x4	Prismatic	4 x F32T8NBF	112	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Troffer	2x4x3	Parabolic	3 x F32T8NBF	86	3 x LMK409	27	LMK409-F-xxxxK-3	1 x SY27W & 3 x SL4100	27	SY27W-3-SL4100-F-xxxxK-T
Troffer	2x4x3	Prismatic	3 x F32T8NBF	86	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY27W & 2 x SL4100	27	SY27W-2-SL4100-F-xxxxK-T
Troffer	2x4x2	Prismatic	2 x F32T8NBF	56	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL400 + Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	2x4x2	Parabolic	2 x F32T8NBF	56	2 x LMK409	18	LMK409-F-xxxxK-2	1 x SY18W & 2 x SL4100	18	SY18W-2-SL4100-F-xxxxK-T
Troffer	2x4x4	Prismatic	4 x F34T12STM	112	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Troffer	2x4x3	Parabolic	3 x F34T12STM	86	3 x LMK409	27	LMK409-F-xxxxK-3	1 x SY27W & 3 x SL4100	27	SY27W-3-SL4100-F-xxxxK-T
Troffer	2x4x3	Prismatic	3 x F34T12STM	86	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY27W & 2 x SL4100	27	SY27W-2-SL4100-F-xxxxK-T
Troffer	2x4x2	Prismatic	2 x F34T12STM	56	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL400 + Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	2x4x2	Parabolic	2 x F34T12STM	56	2 x LMK409	18	LMK409-F-xxxxK-2	1 x SY18W & 2 x SL4100	18	SY18W-2-SL4100-F-xxxxK-T
Troffer	2x4x4	Prismatic	4 x F40T12STM	112	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Troffer	2x4x3	Parabolic	3 x F40T12STM	86	3 x LMK409	27	LMK409-F-xxxxK-3	1 x SY27W & 3 x SL4100	27	SY27W-3-SL4100-F-xxxxK-T
Troffer	2x4x3	Prismatic	3 x F40T12STM	86	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY27W & 2 x SL4100	27	SY27W-2-SL4100-F-xxxxK-T
Troffer	2x4x2	Prismatic	2 x F40T12STM	56	1 x LMK418 + Wire Nut Cover	18	LMK418-F-xxxxK-1	1 x SY18W & 1 x SL400 + Wire Nut Cover	18	SY18W-1-SL4100-F-xxxxK-T
Troffer	2x4x2	Parabolic	2 x F40T12STM	56	2 x LMK409	18	LMK409-F-xxxxK-2	1 x SY18W & 2 x SL4100	18	SY18W-2-SL4100-F-xxxxK-T
Linear Strip	1x4x2		1 x F32T8NBF	57	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Linear Strip	1x4x2		1 x F34T12STM	28	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Linear Strip	1x4x2		1 x F40T12STM	50	1 x LMK409	9	LMK409-F-xxxxK-1	1 x SY09W & 1 x SL4100	9	SY09W-1-SL4100-F-xxxxK-T
Linear Strip	1x8x2		4 x F32T8NBF	112	2 x LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Linear Strip	1x8x2		2 x F59T8NBF	109	2 X LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Linear Strip	1x8x2		2 x F96T12STM60	138	2 X LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Linear Strip	1x8x2		2 x F96T12STM75	173	2 X LMK418	36	LMK418-F-xxxxK-2	1 x SY36W & 2 x SL4100	36	SY36W-2-SL4100-F-xxxxK-T
Linear Strip	1x8x2		2 x F96T12STM95	227	2 X LMK422	44	LMK422-F-xxxxK-2	1 x SY42W & 2 x SL4100	42	SY42W-2-SL4100-F-xxxxK-T
Linear Strip	1x8x2		2 x F96T12STM110	257	2 X LMK422HO	48	LMK422HO-F-xxxxK-2	1 x SY48W & 2 x SL4200	48	SY48W-2-SL4200-F-xxxxK-T

LED Stick Company

3311 County Road 47
Forence, AL 35630
(888) 927-4533
www.ledstick.net
sales@ledstick.net

